



Specifications Ledvance Dulux-L LED 8W - 830 Warm White | 4-Pin - Replaces 18W

[View Product](#)

## General Information

|                          |                                         |
|--------------------------|-----------------------------------------|
| SKU                      | 248035                                  |
| EAN                      | 4058075822054                           |
| manufacturer_code        | 4058075822054                           |
| Brand                    | Ledvance                                |
| Manufacturer Name        | DULUX LED L HF & AC MAINS V 8W 830 2G11 |
| Full box quantity        | 10                                      |
| Any Lamp all-in warranty | 3 Years                                 |
| Energy efficiency class  | E                                       |
| Average Lifetime (h)     | 30000                                   |

## Technical Information

|                             |                 |
|-----------------------------|-----------------|
| Technology                  | LED             |
| Replaces (Watt)             | 18              |
| Wattage                     | 8W              |
| Dimmable                    | Not Dimmable    |
| Cap / Base                  | 2G11 (4-pins)   |
| Number of pins              | 4               |
| Colour Code                 | 830 Warm White  |
| Colour temperature (Kelvin) | 3000 Warm White |
| Colour Rendering (Ra)       | 80-89           |
| Colour of Light             | White           |
| Light Colour Options        | Single Color    |
| Luminous Flux (Lumen)       | 900lm           |

Lumen per watt 112

Product Type Category PL-L / Dulux-L LED

Type of sensor No Sensor

## Lamp Information

Ballast Electronic (HF); Mains (AC) Without Starter

Bulb finish Frosted

Rotatable No

Series Dulux

## Dimensions

Length (mm) 229.5

Diameter (mm) 44

## Why Any-lamp?



Order from the **largest lighting specialist** in Europe



**Customised** quotation



Up to **7 years warranty**



**Easy** return process

